

HEP-Th 9403xxx

February 1994

The zero-curvature representation for nonlinear $O(3)$ sigma-model

A. G. Bytsko *

Steklov Mathematical Institute
Fontanka 27, St.Petersburg 191011
Russia

*Dedicated to Professor L.D. Faddeev
on the occasion of his sixtieth birthday*

Abstract

We consider $O(3)$ sigma-model as a reduction of the principal chiral field. This approach allows to introduce the currents with ultralocal Poisson brackets and to obtain the zero-curvature equation which admits the fundamental Poisson bracket.

*e-mail: bytsko@lomi.spb.su and bytsko@diada.spb.su

Introduction

In present paper we consider one of the field theory models - the nonlinear $O(3)$ sigma-model in the framework of the inverse scattering method. The important step in this approach is to find a zero-curvature representation for the investigated model. An attempt to obtain this representation for $O(3)$ sigma-model was done in paper [1]. But in this paper some extra conditions on components of energy-momentum tensor were imposed. Besides, essential points in [1] were the transition to Sine-Gordon type variables and application of the Backlund transformation. This classically admissible transition is a serious obstacle for using the quantum version of the inverse scattering method.

On the other hand, one may consider $O(3)$ sigma-model as a reduction of a more general model - that of the principal chiral field. The zero-curvature representation for the principal chiral field was obtained in paper [2]. The quantum inverse scattering method was applied to this model in paper [3]. An essential trick in [3] was the change of Poisson brackets for the currents. In present paper we realize this scheme for $O(3)$ sigma-model by means of construction of new pair of currents. But, as we shall see, it is impossible to get the XXX-magnetic model in a way similar to that in the paper [3].

Thus, in present paper new currents are constructed for the investigated model and new $U - V$ pair is obtained via these variables. Also the fundamental Poisson bracket is written out and some properties of new currents are obtained.

1 $\vec{n}$ -field model

The nonlinear $O(3)$ sigma-model (it is also known as $\vec{n}$ -field model) describes a three-dimensional vector $\vec{n} = (n_1, n_2, n_3)$ with components depending on coordinates in (1+1) dimensional space-time. The vector $\vec{n}$ satisfies the space-periodicity condition :

$$\vec{n}(x + L, t) = \vec{n}(x, t)$$

The Lagrangian of the model coincides with Lagrangian of the free field :

$$\mathcal{L} = \frac{1}{2} \int_0^L ((\partial_0 \vec{n})^2 - (\partial_x \vec{n})^2) dx \quad (1)$$

(here we denote : $\partial_0 \equiv \frac{\partial}{\partial t}$; $\partial_x \equiv \frac{\partial}{\partial x}$). We also suppose that the vector $\vec{n}$ satisfies an extra condition - its length is fixed :

$$\vec{n}^2 = n_1^2 + n_2^2 + n_3^2 = 1 \quad (2)$$

The equations of motion following from Lagrangian (1) and respecting constraint (2) are :

$$\partial_0^2 \vec{n} - \partial_x^2 \vec{n} + ((\partial_0 \vec{n})^2 - (\partial_x \vec{n})^2) \vec{n} = 0 \quad (3)$$

For Hamiltonian description of the model we introduce the density of momentum :

$$\vec{\pi} \equiv \frac{\partial \mathcal{L}}{\partial(\partial_0 \vec{n})} = \partial_0 \vec{n}$$

The Legendre transformation of the Lagrangian (1) gives the Hamiltonian of the model :

$$H = \int_0^L (\vec{\pi} \cdot \partial_0 \vec{n}) dx - \mathcal{L} = \frac{1}{2} \int_0^L (\vec{\pi}^2 + (\partial_x \vec{n})^2) dx$$

The Poisson brackets of variables $\vec{\pi}$ and $\vec{n}$ can be obtained from the canonical brackets as Poisson-Dirac brackets with respect to constraints

$$\vec{n}^2 = 1 \quad , \quad \vec{\pi} \cdot \vec{n} = 0$$

These brackets are :

$$\begin{aligned} \{n^a(x), n^b(y)\} &= 0 \quad , \quad \{\pi^a(x), n^b(y)\} = (\delta^{ab} - n^a(x)n^b(x))\delta(x-y) \\ \{\pi^a(x), \pi^b(y)\} &= (\pi^b(x)n^a(x) - \pi^a(x)n^b(x))\delta(x-y) \end{aligned} \quad (4)$$

Because the model is $O(3)$ -invariant, it is more efficient to describe it in terms of variables $\vec{l}$ and $\vec{n}$, where $\vec{l}$ (the angular momentum) is defined as :

$$\vec{l}(x) = \vec{\pi}(x) \wedge \vec{n}(x) \quad , \quad \vec{l}^2(x) = \vec{\pi}^2(x)$$

Here $\wedge$ denotes a vector product : $l^a = \epsilon^{abc}\pi^b n^c$.

The Poisson brackets of these variables

$$\{l^a(x), l^b(y)\} = \epsilon^{abc}l^c(x)\delta(x-y) \quad (5)$$

$$\{l^a(x), n^b(y)\} = \epsilon^{abc}n^c(x)\delta(x-y) \quad (6)$$

$$\{n^a(x), n^b(y)\} = 0 \quad (7)$$

define the current algebra of group $E(3)$. The phase space of the model is a symplectic orbit :

$$\vec{n}^2 = 1 \quad , \quad \vec{l} \cdot \vec{n} = 0 \quad (8)$$

2 Standard zero-curvature representation

The basic method for investigation of models corresponding to different nonlinear equations is the inverse scattering method. Nowadays this is a well developed tool to study classical as well as quantum versions of models (see for example [4]). This method starts from representation of the nonlinear equation in the form of the zero-curvature condition :

$$\partial_t U(x, \lambda) - \partial_x V(x, \lambda) + [U(x, \lambda), V(x, \lambda)] = 0 \quad (9)$$

Here U and V are the same size square matrices with elements depending on space-time variables x and t as well as on some extra spectral parameter λ . Equations (9) have to be satisfied for all values of λ .

Let us consider the principal chiral field model. In this model the dynamical variable $g(x, t)$ takes the values in some compact group G . Equations of motion have the following form :

$$\partial_0^2 g - \partial_x^2 g = \partial_0 g \cdot g^{-1} \cdot \partial_0 g - \partial_x g \cdot g^{-1} \cdot \partial_x g \quad (10)$$

An appropriate $U-V$ pair for this model was found by V.Zakharov and A.Mikhailov [2] in form :

$$U(x, \lambda) = \frac{1}{2} \frac{L_0(x) + L_1(x)}{1 - \lambda} - \frac{1}{2} \frac{L_0(x) - L_1(x)}{1 + \lambda} = \frac{\lambda L_0(x) + L_1(x)}{1 - \lambda^2} \quad (11)$$

$$V(x, \lambda) = \frac{1}{2} \frac{L_0(x) + L_1(x)}{1 - \lambda} + \frac{1}{2} \frac{L_0(x) - L_1(x)}{1 + \lambda} = \frac{\lambda L_1(x) + L_0(x)}{1 - \lambda^2} \quad (12)$$

Here the left currents are introduced, taking the values in Lie algebra of group G :

$$L_0(x, t) = \partial_0 g \cdot g^{-1} \quad , \quad L_1(x, t) = \partial_x g \cdot g^{-1} \quad (13)$$

The zero-curvature condition (9) for $U - V$ pair (11),(12) can be written via these currents L_μ :

$$\partial_0 L_0 - \partial_x L_1 = 0 \quad (14)$$

$$\partial_0 L_1 - \partial_x L_0 + [L_1, L_0] = 0 \quad (15)$$

Let us note that the equation (15) follows from definitions (13):

$$\partial_0(\partial_x g \cdot g^{-1}) - \partial_x(\partial_0 g \cdot g^{-1}) + [\partial_x g \cdot g^{-1}, \partial_0 g \cdot g^{-1}] \equiv 0$$

while equation (14) is a consequence of equations of motion (10).

The Lagrangian and the Hamiltonian can be expressed using the currents L_μ :

$$\mathcal{L} = \frac{1}{4} \int_0^L \text{tr}(L_1^2 - L_0^2) dx \quad ; \quad H = -\frac{1}{4} \int_0^L \text{tr}(L_0^2 + L_1^2) dx \quad (16)$$

Poisson brackets of components of currents L_μ^a are :

$$\{L_0^a(x), L_0^b(y)\} = \epsilon^{abc} L_0^c(x) \delta(x - y) \quad (17)$$

$$\{L_0^a(x), L_1^b(y)\} = \epsilon^{abc} L_1^c(x) \delta(x - y) - \delta^{ab} \delta'(x - y) \quad (18)$$

$$\{L_1^a(x), L_1^b(y)\} = 0 \quad (19)$$

In general case of the principal chiral field with values in the group G the equations of motion (10) admit an extra reduction :

$$g^2(x, t) = I \quad (20)$$

This reduction does not change the form of $U - V$ pair, zero-curvature equations (14),(15) and relations (16). It also preserves the Poisson brackets (17)-(19) because brackets of the currents with the constraint (20) vanish.

Applying the reduction (20) to the case of the principal chiral field for $G = SU(2)$, we obtain the $O(3)$ sigma-model. Indeed, in this case the variable $g(x, t)$ can be written in form :

$$g(x, t) = \vec{n} \cdot \vec{\sigma} \equiv n^a(x, t) \sigma_a \quad , \quad \vec{n}^2 = 1$$

where σ^a are Pauli matrices :

$$\sigma_1 = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \quad , \quad \sigma_2 = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix} \quad , \quad \sigma_3 = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}$$

For given parametrization of $g(x, t)$ equations of motion (10) turn into equations of motion (3) for $\vec{n}$ -field.

Using a relation

$$(\vec{a} \vec{\sigma}) \cdot (\vec{b} \vec{\sigma}) = (\vec{a} \vec{b}) \cdot I + i(\vec{a} \wedge \vec{b}) \cdot \vec{\sigma}$$

we can express the currents $L_\mu = \sum_{a=1}^3 i L_\mu^a \sigma_a$ via variables of $\vec{n}$ -field :

$$L_0(x, t) = i(\partial_0 \vec{n} \wedge \vec{n}) \cdot \vec{\sigma} \equiv i \vec{l} \cdot \vec{\sigma} \quad (21)$$

$$L_1(x, t) = i(\partial_x \vec{n} \wedge \vec{n}) \cdot \vec{\sigma} \quad (22)$$

Thus, if we consider $O(3)$ sigma-model as a reduction of the principal chiral field for group $G = SU(2)$, we immediately obtain a zero-curvature representation for it

with $U - V$ pair given by (11)-(12) and with the equations for currents (14)-(15). As we have mentioned above, one of these equations is a consequence of the equations of motion (3) :

$$\partial_0 L_0 - \partial_x L_1 = i(\partial_0^2 \vec{n} \wedge \vec{n} - \partial_x^2 \vec{n} \wedge \vec{n}) \cdot \vec{\sigma} = i((\partial_0^2 \vec{n} - \partial_x^2 \vec{n}) \wedge \vec{n}) \cdot \vec{\sigma} = 0$$

To apply further the inverse scattering method for solving the $\vec{n}$ -field model one should represent the Poisson brackets of elements of matrix $U(x, \lambda)$ as a fundamental Poisson bracket :

$$\{ \overset{1}{U}(x, \lambda), \overset{2}{U}(y, \mu) \} = [r(\lambda, \mu), \overset{1}{U}(x, \lambda) + \overset{2}{U}(x, \mu)] \delta(x - y) \quad (23)$$

Here $r(\lambda)$ is some classical r -matrix and we use the notations :

$$\overset{1}{U} = U \otimes I, \quad \overset{2}{U} = I \otimes U$$

Unfortunately, since the formula (18) has a term with $\delta'(x - y)$ (so-called nonultralocal term), it is impossible to introduce an appropriate fundamental Poisson bracket.

3 Currents J_μ and new $U - V$ pair

In order to find the new $U - V$ pair which satisfies a zero-curvature representation and has an ultralocal fundamental Poisson bracket we define new current variables :

$$J_0(x, t) = \frac{1}{2}i(\partial_0 \vec{n} \wedge \vec{n} - i\partial_x \vec{n}) \cdot \vec{\sigma} \equiv \frac{1}{2}i(\vec{l} - i\partial_x \vec{n}) \cdot \vec{\sigma} \quad (24)$$

$$J_1(x, t) = \frac{1}{2}i(\partial_x \vec{n} \wedge \vec{n} - i\partial_0 \vec{n}) \cdot \vec{\sigma} \equiv \frac{1}{2}i(\partial_x \vec{n} \wedge \vec{n} - i\vec{\pi}) \cdot \vec{\sigma} \quad (25)$$

It should be noticed here that in case of the group $SU(2)$ the addition of terms like $\frac{1}{2}\partial_\mu g = \frac{1}{2}\partial_\mu \vec{n} \cdot \vec{\sigma}$ to the currents L_μ does not bring them out of Lie algebra $su(2)$. Consequently, J_μ may be regarded indeed as current variables. But if we apply the formulas given above for construction of new currents in case of arbitrary Lie group G , the new objects J_μ will not belong to Lie algebra of this group (but, nevertheless, they will satisfy the zero-curvature equations).

Let us consider an analogue of the pair (11)-(12) for currents J_μ :

$$U'(x, \lambda) = \frac{\lambda J_0(x) + J_1(x)}{1 - \lambda^2}, \quad V'(x, \lambda) = \frac{\lambda J_1(x) + J_0(x)}{1 - \lambda^2} \quad (26)$$

The zero-curvature condition (9) leads to the system of equations :

$$\partial_0 J_0 - \partial_x J_1 = 0 \quad (27)$$

$$\partial_0 J_1 - \partial_x J_0 = [J_0, J_1] \quad (28)$$

Formally, the system (27)-(28) coincides with the system (14)-(15), but it should be noticed that now both equations (27) and (28) follow from the equations of motion (3) :

$$\partial_0 J_0 - \partial_x J_1 = \frac{1}{2}i(\partial_0^2 \vec{n} \wedge \vec{n} - i\partial_{0x} \vec{n} - \partial_x^2 \vec{n} \wedge \vec{n} + i\partial_{x0} \vec{n}) \cdot \vec{\sigma} = \frac{1}{2}i((\partial_0^2 \vec{n} - \partial_x^2 \vec{n}) \wedge \vec{n}) \cdot \vec{\sigma} = 0$$

In order to check the equation (28) one has to write down the new currents J_μ in the form :

$$J_0 = \frac{1}{2}\partial_0 g \cdot g^{-1} + \frac{1}{2}\partial_x g = \frac{1}{2}(L_0 + L_1 g)$$

$$J_1 = \frac{1}{2} \partial_x g \cdot g^{-1} + \frac{1}{2} \partial_0 g = \frac{1}{2} (L_1 + L_0 g)$$

and use the condition of reduction

$$g^2 = (\vec{n} \cdot \vec{\sigma})^2 = \vec{n}^2 \cdot I \equiv I \quad , \quad (29)$$

as well as its consequences

$$g^{-1} = g \quad (30)$$

and

$$L_\mu g = -g L_\mu \quad (31)$$

(The identity (31) was obtained by differentiation of the equation (30))¹

Now l.h.s. of equation (28) may be written in the form

$$\partial_0 J_1 - \partial_x J_0 = \frac{1}{2} (\partial_0 L_1 - \partial_x L_0) + \frac{1}{2} (\partial_0 L_0 - \partial_x L_1) g + \frac{1}{2} (L_0^2 - L_1^2) g \quad ,$$

and taking into account the equations (14)-(15) (in fact this means we use the equations of motion) we come to relation

$$\partial_0 J_1 - \partial_x J_0 = \frac{1}{2} [L_0, L_1] + \frac{1}{2} (L_0^2 - L_1^2) g$$

The r.h.s. of equation (28) may be obtained in the same form using the conditions (29)-(31) :

$$\begin{aligned} [J_0, J_1] &= \frac{1}{4} [L_0 + L_1 g, L_1 + L_0 g] = \frac{1}{4} [L_0, L_1] + \frac{1}{4} [L_0, L_0 g] + \frac{1}{4} [L_1 g, L_1] + \frac{1}{4} [L_1 g, L_0 g] = \\ &= \frac{1}{4} [L_0, L_1] + \frac{1}{4} (L_0^2 g - L_0 g L_0) + \frac{1}{4} (L_1 g L_1 - L_1^2 g) + \frac{1}{4} (L_1 g L_0 g - L_0 g L_1 g) = \\ &= \frac{1}{4} [L_0, L_1] + \frac{1}{2} L_0^2 g - \frac{1}{2} L_1^2 g + \frac{1}{4} [L_0, L_1] g^2 = \frac{1}{2} [L_0, L_1] + \frac{1}{2} (L_0^2 - L_1^2) g \end{aligned}$$

Thus, the difference from case of unreduced principal chiral field is that the second $U' - V'$ pair for $\vec{n}$ -field exists. The next step on the way of the considered model investigation is the calculation of Poisson brackets for new currents.

4 Fundamental Poisson bracket

Now let t^a , $a = 1, 2, 3$ be the basic elements of the algebra $su(2)$. They are supposed to be normalized with respect to the Killing form :

$$tr(t^a t^b) = -\frac{1}{2} \delta^{ab} \quad ; \quad [t^a, t^b] = f^{abc} t^c$$

The generators t^a may be expressed via Pauli matrices :

$$t^a = \frac{1}{2} i \sigma^a \quad ; \quad f^{abc} = -\epsilon^{abc}$$

¹ It is interesting to note, that the relation (31) leads to coincidence of right and left currents in this model :

$$R_\mu \equiv -g^{-1} \cdot \partial_\mu g = \partial_\mu g \cdot g^{-1} \equiv L_\mu \quad .$$

In order to calculate the Poisson brackets of components of the current $J_0(x) = J_0^a(x)t^a$ we use the formulas (5)-(7) ² :

$$\begin{aligned}
\{J_0^a(x), J_0^b(y)\} &= \{l^a(x) - i\partial_x n^a(x), l^b(y) - i\partial_y n^b(y)\} = \\
&= \epsilon^{abc} l^c(x) \delta(x-y) + i\epsilon^{abc} (n^c(x) - n^c(y)) \delta'(x-y) = \\
&= \epsilon^{abc} l^c(x) \delta(x-y) + i\epsilon^{abc} ((x-y)\partial_x n^c(x)) \delta'(x-y) = \\
&= \epsilon^{abc} l^c(x) \delta(x-y) - i\epsilon^{abc} \partial_x n^c(x) \delta(x-y) = \epsilon^{abc} J_0^c(x) \delta(x-y)
\end{aligned} \tag{32}$$

We have also the following relations :

$$\{J_0^a(x), n^b(y)\} = \{l^a(x) - i\partial_x n^a(x), n^b(y)\} = \epsilon^{abc} n^c(x) \delta(x-y) \tag{33}$$

$$\{J_1^a(x), n^b(y)\} = \{(\partial_x \vec{n} \wedge \vec{n} - i\vec{\pi})^a(x), n^b(y)\} = i(n^a(x)n^b(x) - \delta^{ab}) \delta(x-y) \tag{34}$$

In order to obtain the other Poisson brackets it is convenient to use the following relations for currents (let us recall that $\vec{l} \cdot \vec{n} = \vec{\pi} \cdot \vec{n} = \partial_x \vec{n} \cdot \vec{n} = 0$) :

$$i(\vec{J}_1 \wedge \vec{n}) = i(\partial_x \vec{n} \wedge \vec{n} - i\vec{\pi}) \wedge \vec{n} = \vec{\pi} \wedge \vec{n} - i\partial_x \vec{n} = \vec{J}_0 \tag{35}$$

$$i(\vec{J}_0 \wedge \vec{n}) = i(\vec{l} - i\partial_x \vec{n}) \wedge \vec{n} = \partial_x \vec{n} \wedge \vec{n} - i\vec{\pi} = \vec{J}_1 \tag{36}$$

(Here we denote : $\vec{J}_\mu = (J_\mu^1, J_\mu^2, J_\mu^3)$).

Taking into account the relation $\vec{J}_\mu \wedge \vec{n} = -\vec{n} \wedge \vec{J}_\mu$, one may rewrite the formulas (35)-(36) in the following way :

$$J_1 g = -g J_1 = J_0 \tag{37}$$

$$J_0 g = -g J_0 = J_1 \tag{38}$$

Now, using the formulas (32)-(36) we obtain

$$\begin{aligned}
\{J_0^a(x), J_1^b(y)\} &= i\epsilon^{bcd} \{J_0^a(x), J_0^c(y)n^d(y)\} = \\
&= i\epsilon^{bcd} (\epsilon^{acf} J_0^f(x)n^d(y) + \epsilon^{adf} J_0^c(y)n^f(x)) \delta(x-y) = \\
&= i(-J_0^b(x)n^a(x) + J_0^a(x)n^b(x)) \delta(x-y) = \epsilon^{abc} J_1^c(x) \delta(x-y)
\end{aligned} \tag{39}$$

Similarly one can find :

$$\{J_1^a(x), J_1^b(y)\} = \epsilon^{abc} J_0^c(x) \delta(x-y) \tag{40}$$

An important property of brackets (32),(39),(40) is their ultralocality (they do not include terms like $\delta'(x-y)$). This allows us to write down a fundamental Poisson bracket for matrix $U'(x, \lambda)$ in $\vec{n}$ -field model.

Indeed, using (32),(39),(40) and following [4] we find

$$\{ \overset{1}{U'}(x, \lambda), \overset{2}{U'}(y, \mu) \} = -\frac{1}{4} \frac{\sigma^a \otimes \sigma^b}{(1-\lambda^2)(1-\mu^2)} \{ \lambda J_0^a(x) + J_1^a(x), \mu J_0^b(y) + J_1^b(y) \} =$$

² We need also a well known property of generalized functions :

$$(xF(x), \delta'(x)) = -(F(x), \delta(x)) \quad .$$

$$= -\frac{1}{4} \frac{\epsilon^{abc} \sigma^a \otimes \sigma^b}{(1-\lambda^2)(1-\mu^2)} ((\lambda\mu+1)J_0^c(x) + (\lambda+\mu)J_1^c(x)) \delta(x-y)$$

Now, introducing the permutation operator

$$P = \frac{1}{2}(I \otimes I + \sigma^a \otimes \sigma^a)$$

and using its property

$$\epsilon^{abc} \sigma^a \otimes \sigma^b = -i [P, \sigma^c \otimes I] = -2[P, t^c \otimes I] ,$$

we obtain

$$\begin{aligned} \{ \overset{1}{U}'(x, \lambda), \overset{2}{U}'(y, \mu) \} &= \frac{[P, (\lambda\mu+1)\overset{1}{J}_0(x) + (\lambda+\mu)\overset{1}{J}_1(x)]}{2(1-\lambda^2)(1-\mu^2)} \delta(x-y) = \\ &= \frac{1}{(1-\lambda^2)(1-\mu^2)} \left[\frac{P}{2(\lambda-\mu)}, (\lambda^2-1)\mu\overset{1}{J}_0(x) + (1-\mu^2)\lambda\overset{1}{J}_0(x) + (\lambda^2-1)\overset{1}{J}_1(x) + \right. \\ &\quad \left. + (1-\mu^2)\overset{1}{J}_1(x) \right] \delta(x-y) = \left[\frac{P}{2(\lambda-\mu)}, \overset{1}{U}'(x, \lambda) - \overset{1}{U}'(x, \mu) \right] \delta(x-y) = \\ &= \left[\frac{P}{2(\lambda-\mu)}, \overset{1}{U}'(x, \lambda) + \overset{2}{U}'(x, \mu) \right] \delta(x-y) \end{aligned}$$

So, we have found the fundamental Poisson bracket for matrix $U'(x, \lambda)$ with the following r -matrix :

$$r(\lambda, \mu) = \frac{P}{2(\lambda-\mu)}$$

We have succeeded to find the fundamental Poisson brackets due to the observation that the transition from standard currents L_0 and L_1 (which correspond by formulas (21)-(22) to the pair of variables $\vec{l}$ and $\partial_x \vec{n} \wedge \vec{n}$) to currents J_0 and J_1 leads to disappearance of the term with $\delta'(x-y)$ in Poisson brackets. At first sight, however, this disappearance looks quite unexpected. It may be explained by the fact that new currents are not deformations of standard currents.

Indeed, if one takes the initial Hamiltonian with an extra parameter γ :

$$H = \frac{1}{2} \int_0^L (\vec{\pi}^2 + \gamma^2 (\partial_x \vec{n})^2) dx ,$$

he will obtain the following standard and new currents :

$$\vec{L}_0(x) = \vec{l}(x) \quad ; \quad \vec{L}_1(x) = \gamma \partial_x \vec{n} \wedge \vec{n}$$

$$\vec{J}_0(x) = \vec{l}(x) - \gamma \partial_x \vec{n} \quad ; \quad \vec{J}_1(x) = \gamma \partial_x \vec{n} \wedge \vec{n} - i\vec{\pi} = -i(\vec{\pi} + i\gamma \partial_x \vec{n} \wedge \vec{n})$$

These formulas imply that one can consider the currents J_0 and J_1 as deformations with parameter γ of variables $\vec{l}$ and $-i\vec{\pi}$. One can come to the same conclusion simply comparing the relations (32),(39),(40) for J_0 and J_1 with formulas (4)-(5) for $\vec{l}, \vec{\pi}$.

5 Lagrangian, Hamiltonian and currents $\hat{J}_\mu$

As was mentioned above, the Lagrangian as well as the Hamiltonian of $\vec{n}$ -field may be written via currents L_μ :

$$\mathcal{L} = \frac{1}{4} \int_0^L \text{tr}(L_1^2 - L_0^2) dx = \frac{1}{2} \int_0^L (\vec{l}^2 - (\partial_x \vec{n} \wedge \vec{n})^2) dx \quad (41)$$

$$H = -\frac{1}{4} \int_0^L \text{tr}(L_0^2 + L_1^2) dx = \frac{1}{2} \int_0^L (\vec{l}^2 + (\partial_x \vec{n} \wedge \vec{n})^2) dx \quad (42)$$

It turns out that the analogous formulas can be obtained in terms of new currents J_μ . Indeed, if we consider the Lagrangian :

$$\begin{aligned} \mathcal{L}' &= \frac{1}{2} \int_0^L \text{tr}(J_1^2 - J_0^2) dx = \int_0^L \text{tr} J_1^2 dx = - \int_0^L \text{tr} J_0^2 dx = \\ &= \frac{1}{2} \int_0^L (\vec{l} - i\partial_x \vec{n})^2 dx = \frac{1}{2} \int_0^L (\vec{l}^2 - (\partial_x \vec{n})^2) dx - i \int_0^L (\vec{l} \cdot \partial_x \vec{n}) dx \end{aligned} \quad (43)$$

it will differ from the initial Lagrangian (1). But the difference of these Lagrangians

$$\Theta = \mathcal{L}' - \mathcal{L} = i \int_0^L (\vec{l} \cdot \partial_x \vec{n}) dx = i \int_0^L (\partial_x \vec{n} \wedge \partial_0 \vec{n}) \cdot \vec{n} dx$$

coincides with so-called topological term which does not give a contribution into the variation of the action (see for example [5]). Indeed :

$$S_\Theta = \int_{t_1}^{t_2} \Theta dt = i \int_{t_1}^{t_2} (d\vec{n} \wedge d\vec{n}) \vec{n} \equiv i \int_{t_1}^{t_2} \Omega$$

and, since the form Ω is closed $d\Omega = 0$, it leads to $\delta S = i \int_{t_1}^{t_2} d\Omega = 0$. Thus, the Lagrangians $\mathcal{L}'$ and $\mathcal{L}$ are equivalent.

The Hamiltonian of the model may be written in form :

$$H = - \int_0^L \text{tr} J_0 \hat{J}_0 dx = \int_0^L \text{tr} J_1 \hat{J}_1 dx = \frac{1}{2} \int_0^L (\vec{l}^2 + (\partial_x \vec{n})^2) dx$$

Here we introduce one more pair of currents which up to the sign are Hermitian conjugations of currents J_μ :

$$\hat{J}_0(x, t) \equiv -J_0^*(x, t) = \frac{1}{2} i(\vec{l} + i\partial_x \vec{n}) \cdot \vec{\sigma} \quad (44)$$

$$\hat{J}_1(x, t) \equiv -J_1^*(x, t) = \frac{1}{2} i(\partial_x \vec{n} \wedge \vec{n} + i\vec{\pi}) \cdot \vec{\sigma} \quad (45)$$

One may easily check that the currents $\hat{J}_\mu$ satisfy the zero-curvature equations (27)-(28), while equations (37)-(38) turn into the equations :

$$g \hat{J}_1 = - \hat{J}_1 g = \hat{J}_0 \quad (46)$$

$$g \hat{J}_0 = - \hat{J}_0 g = \hat{J}_1 \quad (47)$$

The Poisson brackets of currents $\hat{J}_\mu$ exactly repeat the formulas (32),(39),(40) :

$$\begin{aligned} \{\hat{J}_0^a(x), \hat{J}_0^b(y)\} &= \epsilon^{abc} \hat{J}_0^c(x) \delta(x-y) \\ \{\hat{J}_0^a(x), \hat{J}_1^b(y)\} &= \epsilon^{abc} \hat{J}_1^c(x) \delta(x-y) \\ \{\hat{J}_1^a(x), \hat{J}_1^b(y)\} &= \epsilon^{abc} \hat{J}_0^c(x) \delta(x-y) \end{aligned} \quad (48)$$

But, as one should expect, the Poisson brackets of currents J_μ with $\hat{J}_\mu$ contain nonultralocal terms :

$$\begin{aligned}\{J_0^a(x), \hat{J}_0^b(y)\} &= \epsilon^{abc} l^c(x) \delta(x-y) - i\epsilon^{abc}(n^c(x) + n^c(y)) \delta'(x-y) = \\ &= \epsilon^{abc} J_0^c(x) \delta(x-y) - 2i\epsilon^{abc} n^c(x) \delta'(x-y)\end{aligned}$$

$$\{J_0^a(x), \hat{J}_1^b(y)\} = \epsilon^{abc} \hat{J}_1^c(x) \delta(x-y) - 2\delta^{ab} \delta'(x-y)$$

$$\{\hat{J}_0^a(x), J_1^b(y)\} = \epsilon^{abc} J_1^c(x) \delta(x-y) - 2\delta^{ab} \delta'(x-y)$$

One should notice that the presence of currents $\hat{J}_\mu$ together with J_μ in the Hamiltonian is quite natural. Indeed, one can obtain four new variables from standard currents L_μ :

$$\begin{aligned}J_0 &= \frac{1}{2}(L_0 + L_1 g) \quad , \quad J_1 = \frac{1}{2}(L_1 + L_0 g) \\ \hat{J}_0 &= \frac{1}{2}(L_0 - L_1 g) \quad , \quad \hat{J}_1 = \frac{1}{2}(L_1 - L_0 g)\end{aligned}$$

As we can conclude from relations (37)-(38) and (46)-(47) the pair J_0, J_1 as well as the pair $\hat{J}_0, \hat{J}_1$ are not, in fact, independent variables. So, in general case, in order to keep the number of independent variables one has to use, for example, the pair of currents $J_0, \hat{J}_0$. And from this point of view, it is rather unexpected that formulas for $U - V$ pair and expression for Lagrangian contain, in fact, only one independent current.

Here we may give as illustrations the following expressions for $U - V$ pair :

$$\begin{aligned}U'(\lambda) &= \frac{\lambda J_0(x) + J_1(x)}{1 - \lambda^2} = J_0(g + \lambda)[(g - \lambda)(g + \lambda)]^{-1} = J_0(g - \lambda)^{-1} = -(g + \lambda)^{-1} J_0 \\ V'(\lambda) &= \frac{\lambda J_1(x) + J_0(x)}{1 - \lambda^2} = J_1(g - \lambda)^{-1} = -(g + \lambda)^{-1} J_1\end{aligned}$$

Finally, we note that if we replace in formulas (26) the currents J_μ with the currents $\hat{J}_\mu$, it will give us one more pair of matrices $U''(x, \lambda), V''(x, \lambda)$ satisfying the zero-curvature equation. It follows from the relation (48) that the matrix $U''(x, \lambda)$ will have the same fundamental Poisson bracket and r -matrix as the matrix $U'(x, \lambda)$ has.

6 Light-cone coordinates

Since the Lagrangian (1) is relativistically invariant, it is natural to use light-cone coordinates

$$\xi = \frac{t + x}{2} \quad , \quad \eta = \frac{t - x}{2}$$

It is convenient to introduce simultaneously new variables :

$$J_+(x, t) = \sum_{a=1}^3 J_+^a t^a = \frac{1}{2}(J_0(x, t) + J_1(x, t)) = \frac{1}{4} \partial_\xi g \cdot g^{-1} + \frac{1}{4} \partial_\xi g$$

$$J_-(x, t) = \sum_{a=1}^3 J_-^a t^a = \frac{1}{2}(J_0(x, t) - J_1(x, t)) = \frac{1}{4} \partial_\eta g \cdot g^{-1} - \frac{1}{4} \partial_\eta g$$

It follows from (37)-(38) that

$$J_+ g = -g J_+ = J_+ \quad (49)$$

$$g J_- = -J_- g = J_- \quad (50)$$

Using (32),(39),(40) we get :

$$\{J_+^a(x), J_+^b(y)\} = \epsilon^{abc} J_+^c(x) \delta(x-y) \quad (51)$$

$$\{J_-^a(x), J_-^b(y)\} = \epsilon^{abc} J_-^c(x) \delta(x-y) \quad (52)$$

$$\{J_+^a(x), J_-^b(y)\} = 0 \quad (53)$$

Now, following the paper [3], we may consider the variables S and T as a pair of independent spin variables. In [3] the transition from principal chiral field model to XXX-magnetic model was performed on this way, and the well-developed approach of the Bethe ansatz was used for further investigation.

But in our case this scheme cannot be applied directly. Indeed, one can obtain from (35)-(38) the following relations :

$$J_0^2 = -J_1^2 \quad (54)$$

$$J_0 J_1 = -J_0 g J_0 = -J_1 J_0 \quad (55)$$

From these relations we immediately conclude :

$$S^2 \equiv J_+^2 = \frac{1}{4}(J_0 + J_1)^2 = 0 \quad , \quad T^2 \equiv J_-^2 = \frac{1}{4}(J_0 - J_1)^2 = 0 \quad (56)$$

Thus, the Casimir operators corresponding to the spin variables $\vec{S}$ and $\vec{T}$ have zero values. This fact does not allow us to use the Bethe ansatz approach as it was done in [3].

Let us note that relation (60) gives some extra condition when solving an auxiliary system of differential equations. In our case taking into account the concrete form of matrices $U'(x, \lambda)$ and $V'(x, \lambda)$ (26) and using light-cone coordinates, we can write down the auxiliary problem as follows

$$\partial_\xi \vec{F} = \frac{2}{1-\lambda} J_+ \vec{F} \quad , \quad \partial_\eta \vec{F} = \frac{2}{1+\lambda} J_- \vec{F} \quad (57)$$

The relations (60) lead to the extra conditions :

$$J_+ \partial_\xi \vec{F} = 0 \quad , \quad J_- \partial_\eta \vec{F} = 0 \quad (58)$$

Using the relations (49)-(50), one can rewrite the same conditions in the form :

$$(g+1)\partial_\xi \vec{F} = 0 \quad , \quad (g-1)\partial_\eta \vec{F} = 0$$

Finally, let us note that the relations (57),(58) allow to write down the second order differential equations for vector $\vec{F}$:

$$\partial_\xi^2 \vec{F} = \frac{2}{1-\lambda} (\partial_\xi J_+) \vec{F} \quad , \quad \partial_\eta^2 \vec{F} = \frac{2}{1+\lambda} (\partial_\eta J_-) \vec{F} \quad (59)$$

7 Conclusion

Thus, as it was shown above, the fact that obtained currents $\vec{J}_+$, $\vec{J}_-$ have the zero lengths does not allow to apply a standard scheme of quantization. But the same fact points out another possible approach for the investigation of the model - that of the transition to fermion-type variables. Indeed, if we write down the currents $\vec{J}_+$, $\vec{J}_-$ as follows

$$\vec{J}_+ = \frac{1}{2} \begin{pmatrix} i(z_1^2 - \bar{z}_1^2) \\ z_1^2 + \bar{z}_1^2 \\ 2iz_1 \bar{z}_1 \end{pmatrix}, \quad \vec{J}_- = \frac{1}{2} \begin{pmatrix} i(z_2^2 - \bar{z}_2^2) \\ z_2^2 + \bar{z}_2^2 \\ 2iz_2 \bar{z}_2 \end{pmatrix}$$

where $z_1(x)$ and $z_2(x)$ are the components of the spinor $\Psi(x)$ with the Poisson brackets :

$$\{z_i(x), \bar{z}_j(y)\} = \delta_{ij} \delta(x - y)$$

we will easily check the formulas (51)-(53) and the relation :

$$(\vec{J}_+)^2 = (\vec{J}_-)^2 = 0 \quad (60)$$

Thus, in principle one is able to quantize the $\vec{n}$ -field model by means of the fermionization of current variables. We are going to perform a more detailed investigation in the forthcoming paper.

Acknowledgements

I am very grateful to L.D. Faddeev for permanent supervision. I would like to thank M.A. Semenov-Tian-Shansky for useful discussions.

References

1. K. Pohlmeyer. Integrable Hamiltonian Systems and Interactions through Quadratic Constraints .- Comm.Math.Phys. v.46 No.3 (1976), pp.207-221
2. V.E. Zakharov, A.V. Mikhailov.- Sov.Phys. JETP (Engl.Transl) 74 (1978), p.1017
3. L.D. Faddeev, N.Yu. Reshetikhin. Integrability of the Principal Chiral Field Model in 1+1 Dimension.- Annals of Physics, 167 (1986), pp.227 - 256
4. L.D. Faddeev, L.A. Takhtajan. Hamiltonian methods in the theory of solitons. Springer-Verlag, 1986.
5. L.D. Faddeev. In quest of the multidimensional solitons. In book: Nonlocal, nonlinear and nonrenormalizable field theories. (IV Conference on nonlocal field theories. USSR, Alushta, 1976) (In Russian) pp.207-223 (Engl. Transl. to be published in Advanced Series in Math.Phys.)